

SPECIFICATIONS

Low DOP ASE Broadband Source DL-ASE-CW-CSCL117A

The information contained in these documents is confidential, privileged and it may not be reproduced in whole, or in part, nor may any of the information contained therein be disclosed without the prior consent from DenseLight in writing. DenseLight reserves the right to make product design or specifications changes without notice

A. PRODUCT DESCRIPTION

The DenseLight DL-ASE-CW-CSCL117A is a series Low DOP ASE broadband source for fiber optic gyroscope, fiber optic sensor, optical test instrument and optical coherence tomography. This DL-ASE-CW-CSCL117A consists of a DenseLight standard ASE broadband source, a temperature controller and a built-in current driver capable for CW driving, which can be customized with various options to meet your specific needs.

B. FEATURES

- Ex-fiber output power of >11 dBm
- Spectral power density >-15 dBm/nm over 1525 to 1610nm
- Low Degree of Polarization
- Single mode fiber output
- Integrated optical isolator
- Highly stable power output with active power control
- Built-in current driver and temperature controller
- Over temperature protection and internal PCB temperature monitor
- Single +5V power supply (optional power adapter)
- High wall-plug efficiency
- Compact size
- RoHS Compliance
- Telcordia Qualified broadband source (GR-468-CORE)


C. APPLICATIONS

- Optical Test Instrument
- Fiber Optic Sensors
- Fiber Optic Communications
- Optical Coherence Tomography
- Biomedical Imaging Device
- Clinical Healing Equipment

The information contained in these documents is confidential, privileged and it may not be reproduced in whole, or in part, nor may any of the information contained therein be disclosed without the prior consent from DenseLight in writing. DenseLight reserves the right to make product design or specifications changes without notice


D. PHYSICAL DIMENSIONS AND MECHANICAL SPECIFICATION

Dimension: L100 x W80 x H16 mm
 Enclosure: Metal Case
 Optical output: 1 m SMF-28 fiber, 900um loose tube with FC/APC
 Cooling: Air-cooled.
 Electronic interface: 10-way single row HE14 shrouded header



The information contained in these documents is confidential, privileged and it may not be reproduced in whole, or in part, nor may any of the information contained therein be disclosed without the prior consent from DenseLight in writing. DenseLight reserves the right to make product design or specifications changes without notice

E. PIN ASSIGNMENT AND FUNCTION



HE14 Shrouded Header Pin Layout (Pin 1 near to SMF output)

Pin Assignment

Pin No.	Symbol	Power/Control /Monitor	Analog /Digital	Input /Output	Description
1	P _{GN} D	P			Power Supply Ground
2	P _{GN} D	P			Power Supply Ground
3	V _S	P			+5V d.c.
4	V _S	P			+5V d.c.
5	OVRT	M	D	O	To report PCB over temperature and internal self-protection shutdown in operation (Active high)
6	T _{MON}	M	A	O	To monitor the temperature of PCB
7	P _{MON1}	M	A	O	To monitor the PD current in ASE1
8	P _{MON2}	M	A	O	To monitor the PD current in ASE2
9	LO_EN	C	D	I	To enable Light output (active low or no connection to enable light driver)
10	A _{GN} D				Signal ground for control and monitor signals

The information contained in these documents is confidential, privileged and it may not be reproduced in whole, or in part, nor may any of the information contained therein be disclosed without the prior consent from DenseLight in writing. DenseLight reserves the right to make product design or specifications changes without notice

F. ABSOLUTE MAXIMUM RATINGS

Parameter	Symbol	Condition	Min	Max	Unit
Operating temperature (case) ¹	T _{op}	I _{op}	0	60	°C
Operating Relative Humidity ²	RH	I _{op}	-	85	%
Storage temperature	T _{stg}	Unbiased	-40	85	°C
Input current	I _s		-	6	A

1) Air flow rate of 0.5m/s

2) Non-condensing

G. ELECTRICAL SPECIFICATIONS³

Parameter	Symbol	Condition	Min	Typ	Max	Unit
Input Power Supply	V _S	-	4.75	5	5.5	V
Input Current	I _S	-	-	-	2	A
Total Power consumption	P _S	-	-	-	10	W
Analog Output Monitor - Pin No 6						
Voltage	V _{OUT}	R _X = infinite	0	-	2.5	V
Output Impedance	R _{OUT}	-	-	150	-	Ω
Source Current	I _{OUT}	V _{OUT} = 2.5V	-	-	4	mA
Analog Input Control - Pin No 9						
Voltage	P _{SET}	-	0.3	-	2.5	V
Input Impedance	R _{IN}	-	-	10	-	kΩ
Sink Current	I _{IN}	V _{IN} = 2.5V	-	2.5	-	mA
Internal PCB Temperature Monitor	T _{MON}	Analog voltage: T _{MON} = 395mV + (6.2mV/°C x T), T = PCB temperature in °C				mV
Power Output Monitor	P _{MON}	Analog output: P _{MONx} ~ 1.5V x (P _o / P _{rated}), P _o and P _{rated} in mW				V
Voltage	V _{OUT}	R _X = infinite	0		3.0	V
Output Impedance	R _{OUT}			150		□
Source Current	I _{OUT}	V _{OUT} = 3.0V			4	mA
Light Output Enable	LO-EN	Digital input with internal 10K pull-down for light output enable at logic low or no connection				
	V _{IL}	Normal	0		1	V
	V _{IH}	Disable light output	2.5		3.3	V

3) Unless otherwise specified, tests are performed at T_{op} = 25°C.


The information contained in these documents is confidential, privileged and it may not be reproduced in whole, or in part, nor may any of the information contained therein be disclosed without the prior consent from DenseLight in writing. DenseLight reserves the right to make product design or specifications changes without notice

H. OPTICAL SPECIFICATIONS⁴

Parameter	Symbol	Min	Typ	Max	Unit
Power output	P _o	11			dBm
Power density @ 1525 to 1610nm	P _{density}	-15			dBm/nm
Bandwidth @ 3dB	B _{FWHM}	55			nm
Degree of polarization	DOP			5	%
Output stability ⁽⁴⁾ 1 hour	Stb			± 0.05	dB
8 hours				± 0.1	dB

⁴⁾ After one hour of warm-up

I. TYPICAL OPTICAL PERFORMANCE




Spontaneous Emission Spectrum

The information contained in these documents is confidential, privileged and it may not be reproduced in whole, or in part, nor may any of the information contained therein be disclosed without the prior consent from DenseLight in writing. DenseLight reserves the right to make product design or specifications changes without notice

J. APPLICATION INFORMATION

A. Typical Application Circuit



B. Power Supply Requirement and Connections

The power supply must be capable of supplying the maximum input current (I_S) as given in the electrical specification table at all times during operation. This is because during transients (eg. switching on the light source or with a sudden change in operating ambient temperature), the ASE broadband Source will require a momentary higher current from the power supply compared to its steady-state operation.

The two cables to the two V_S pins (Pin 3 and Pin 4) should be shorted at the positive terminal of the power supply as shown in the Typical Application Circuit. This is to divide the total current load to the broadband source between the two cables. Similarly, the two cables to the P_{GND} pins (Pin 1 and Pin 2), as well as the cable to the A_{GND} pin (Pin 10) should be shorted at the ground of the power supply terminal.

The information contained in these documents is confidential, privileged and it may not be reproduced in whole, or in part, nor may any of the information contained therein be disclosed without the prior consent from DenseLight in writing. DenseLight reserves the right to make product design or specifications changes without notice

C. Selection of Resistance R_X for Analog Monitor Signals

In the Typical Application Circuit given, the function of R_X is to increase the current in the signal cables so as to reduce the effect of environmental noise on the analog monitor signals. In a noisy environment, the value of R_X is recommended to be $1k\Omega$. By choosing R_X to be $1k\Omega$, the actual voltage measured at the buffer output will be reduced due to loading effect, as compared to when R_X is infinite.

$$V_{\text{BUFFER OUTPUT}} = \frac{R_X}{R_X + 150} \times V_{\text{OUT}}$$

where R_X is resistance in Ω

In a non-noisy environment, the value of R_X can be increased to reduce loading effect. It is not recommended to choose R_X less than $1k\Omega$.

For further technical information, please refer to DenseLight Semiconductor ASE1 Broadband Source User Operation Manual.

The information contained in these documents is confidential, privileged and it may not be reproduced in whole, or in part, nor may any of the information contained therein be disclosed without the prior consent from DenseLight in writing. DenseLight reserves the right to make product design or specifications changes without notice